

## PS-102R Remote Control Switch



102R is a wireless remote control switch that includes a receiver and handheld remote controllers. The four buttons on the controller can control two groups of relay output independently, and each group has one normal open and one normal close contact. It can be used to control electric lock, electric device, alarm panel and panic switch. The receiver and controller will match with each other by simply setting the same DIP switch code. Each receiver can be controlled by unlimited quantity of controllers.



Button	Reaction
ON:	Press button, Relay 1 ON
PULSE:	Press button, Relay 2 momentary output
OFF:	Press button, Relay 1,2 OFF
PANIC:	Press button, Relay 2 ON

### Specification

Receiver Power Source	DC 11-15V
Transmitter Power Source	DC 12V alkaline battery(A23)
Effective Distance	100M (open space)
Working Frequency	380 MHZ (RF)
Code Combination	8-Bit (Codes can be programmed by yourself)
Relay Output	1 N.O. and 1 N.C.
Relay Contact	5A/120VAC
Package	One set includes one receiver and two transmitters
Additional transmitter model	PS-102P
Maximum number of transmitter	Unlimited
Receiver Dimension	114W x 64L x 33Dmm
Transmitter Dimension	37W x 60L x 15Dmm