

The PS-453 Remote control can be used to arm and disarm the wired alarm panel remotely by using PS-415 wireless receiver. Additional panic button is also included.

This series works on the "hopping code system" so it has no dip switch setting and can be installed within seconds and able to accept a rotation of over 1,000,000 different system code combinations.



FEATURES

- First button for Panic.
- Second button for Home Armed / Disarmed.
- Third button for Away (fully) Armed / Disarmed.
- Forth button for spare
- LED indicates signal transmission OK and flashes twice every 15 seconds upon low battery condition.

SPECIFICATIONS

Power source	DC3V CR2032 battery.
Battery Life	Over 5 year according to usage condition and battery quality
Working temperature	-10°C to 40°C.
Transmitting Current	8mA.
Frequency	433 MHZ
Hopping Code System	1,000,000 combination codes
Dimensions	85L x 28W x 14H (mm).
Stand-by current	0uA.
Weight	20g (battery not included).