

Voice Dialer

FEATURES

1. Easy installation
2. No volt memory IC
3. Two zones input (N.C or N.O)
4. Two outgoing voice messages



SPECIFICATION

Model	PS-711B
Power Supply	DC12V input jack with plug attached
Standby Current	20mA
Operating Current	60mA
Trigger Input method	Two zones N.C. or N.O input
Exit delay	Instant or 120 seconds
Entry Delay	Instant or 30 seconds
Mode button	<ol style="list-style-type: none"> 1. Programming mode- to program telephone and voice recording 2. Checking present status (OPEN/CLOSE) of trigger input #1 & #2 3. Operate arm / disarm
Memory Button	For recording and displaying telephone number
Voice Button	For recording and playing voice message
Voice message	10 second for each zone input, total 20 seconds
Number of telephone Stored	Up to 4
Telephone format	Accept both tone and pulse
Telephone system	Accept both single or PABX system
Max Digit per tel number	32 digits
Dialing method	<ol style="list-style-type: none"> 1. To dial 2 times for each answered telephone and redial up to 8 times for each busy or unanswered telephone whether the alarm is reset or not. 2. Stop dialing upon alarm reset.
Siren Output	Output jack with plug attached
Microphone	Built-in microphone
LCD Indication	To show status and test telephone number
Speaker	Built in speaker for testing and playback of voice message
Data Memory	No volt memory IC
Back Up Battery	9V back up battery can be added to ensure operation under power failure
Operating Temperature	-20 to 50 ⁰ C
Case	Ivory ABS plastic
Weight	260 g
Dimension WxHxD	146x101x38 mm